

AMENDMENT TO THE CLAIMS

1. ~~1.~~ (currently amended) A ~~circuit for a~~ radar level gauge for measuring the level of the surface of a product stored in a container, said level gauge including

a radar ~~module for transmitting~~ generating microwave signals ~~on at least two different frequency bands,~~

~~from a multiband antenna unit transmitting said microwave signals towards~~ said surface and for receiving by ~~said same antenna unit~~ microwave signals reflected by said surface, and

~~a measuring and controlling unit for determining the level based on an evaluation of the time lapsed between the received and the transmitted signals and~~ said radar ~~operating on at least two different frequency bands,~~

~~said radar module including wherein the circuit includes:~~

- ~~first microwave provision means~~ a microwave generating source for providing a first microwave signal of a first frequency band having a first center frequency,
- ~~second microwave provision means~~ at least one frequency multiplier coupled between said microwave generating source and said antenna unit for providing a second microwave signal of a second frequency band having a second center frequency, wherein the ratio between the second and the first center frequency is quantified as at least greater than 1.5:1 and preferably greater than 2:1 and
- switches operated by means of a control signal for switching the circuit to operate on said first frequency band or said second frequency band.

2. (currently amended) A circuit according to claim 1, wherein the circuit further includes:

~~a microwave generating source operating on a fixed frequency for~~

~~at least one frequency multiplier coupled between the source and the antenna unit for the provision at the output of the frequency multiplier a multiple~~

frequency multipliers

- a number of first switches for the choice of an operating frequency ( $f_0$ ,  $mf_0$ ) to be delivered to the antenna unit,
- a number of mixers for mixing the microwave signal received from the antenna unit with the chosen operating frequency for the forming of an IF-frequency,
- a number of second switches for directing the microwave operating frequency to a mixer corresponding to the operating frequency and
- the choice of operating frequency for the circuit is made by a control signal controlling the switches.

3. (previously presented) The circuit according to claim 2, including:

- a chain of at least two frequency multipliers coupled in series between the source and the antenna unit.

4. (previously presented) The circuit according to claim 2, including:

- a chain of at least two cascade coupled frequency multipliers coupled between the source and the antenna unit.

5. (previously presented) The circuit according to claim 3, including:

- each one of said multiplier multiplying the input microwave frequency by a predetermined constant.

6. (previously presented) The circuit according to claim 4, including:

- each one of said multiplier multiplying the input microwave frequency by a predetermined constant.

7. (previously presented) The circuit according to claim 2, wherein said microwave generating source includes a voltage control oscillator VCO.

8. (previously presented) The circuit according to claim 7, wherein said microwave generating source includes a phase locked loop.

9. (currently amended) A method for measuring the level of the surface of a product stored in a container by means of a radar level gauge, wherein said level gauge includes a radar for transmitting microwave signals from a multiband antenna unit towards said surface for receiving by said same antenna unit microwave signals reflected by said surface and for determining the level based on an evaluation of the time lapsed between the received and the transmitted signals and said radar operating on at least two different frequency bands, comprising the steps of:

- ~~using a microwave generating source for providing a first microwave signal of a first frequency band having a first center frequency,~~
- ~~- providing in a circuit a microwave signal of a first frequency band having a first center frequency~~
- ~~multiplying, in at least one frequency multiplier coupled between said microwave generating source and said antenna unit, said first microwave signal for providing in said circuit a second microwave signal of a second frequency band having a second center frequency, wherein the ratio between the second and the first center frequency is quantified as at least greater than 1.5:1 and preferably greater than 2:1,~~
- providing said circuit with switches for switching the circuit to operate on said first frequency band or said second frequency band and
- controlling said switches by means of a control signal.

10. (currently amended) The method according to claim 9, further comprising the step of:

- generating a microwave having a fixed frequency  $f_0$ ,
- multiplying in said at least one frequency multiplier said fixed frequency  $f_0$  by a factor  $m$  for obtaining a frequency  $mf_0$  being the factor  $m$  higher than said

fixed frequency,

- choosing by means of controlling a number of first switches an operating frequency ( $f_0$ ,  $mf_0$ ) to be delivered to the antenna unit,
- directing the microwave operating frequency to a mixer corresponding to the operating frequency,
- mixing the microwave signal received from the antenna unit with the chosen operating frequency for the forming of an IF-frequency and
- selecting an operating frequency for the circuit by means of said control signal controlling said switches.

11. (previously presented) A radar level gauge, characterized in that it comprises the circuit according to claim 1.

12. (new) The circuit according to claim 1, wherein said switches comprise a switch for selectively connecting said first or said second microwave signal to said antenna.

13. (new) The circuit according to claim 1, further comprising:

- a first and a second mixer connected to receive the reflected microwave signal from the antenna unit, for forming an intermediate frequency (IF signal),
- a first power divider for directing a portion of said first microwave signal to said first mixer,
- a second power divider for directing a portion of said second microwave signal to said second mixer.

14. (new) The circuit according to claim 13, wherein said switches comprise a switch for connecting a selected one of said mixers to said antenna unit.

15. (new) The circuit according to claim 1, wherein the ratio between the second and the first center frequency is quantified as at least greater than 1.5:1 and preferably greater than 2:1.

16. (new) The method according to claim 9, wherein the ration between the second and the first center frequency is quantified as at least greater than 1.5:1 and preferably greater than 2:1.